CRAFTSMAN®

2300 WATTS 3000 STARTING WATTS

INVERTER GENERATOR



2300 WATTS 3000 STARTING WATTS

INVERTER GENERATOR

Start your favorite motor-driven essentials using quiet and clean power you can take anywhere. The new CRAFTSMAN 3000 portable inverter generator features a boost of power with 50 percent more starting capacity so you can do more with a smaller product. With an Ultra Quiet and high-performance design, it's the perfect on-the-go solution for camping, tailgating and other outdoor activities.



BUILT IN HANDLE
Easy mobility; carry with one hand

STEADY POWER
Our technology makes safe, clean power for your electronics

EASY START
Start/Stop/Choke dial makes starting quick and easy

BOOST OF POWER
50 percent more starting capacity allows you to do more with a smaller product

ULTRA QUIET DESIGN WITH HIGH PERFORMANCE
Perfect for camping and tailgating

BOOST OF POWER™

ULTRA QUIET™

EASY MOBILITY™

3 YEAR™ LIMITED WARRANTY
WE BUILD PRIDE!™

If a product fails to perform due to defects in material or workmanship, we will repair or replace it. Proof of purchase required. 90 Day Satisfaction Guarantee. See CRAFTSMAN.com or call 888-331-4569 for details.

HOW MUCH POWER DO YOU NEED?

Sizing a portable generator is easy. Check out this sample:

1 CHOOSE WHICH DEVICES YOU WANT TO POWER AT THE SAME TIME.

2 RECORD AND ADD THE RUNNING WATTS LISTED FOR EACH DEVICE THAT YOU NEED TO POWER.

3 ADD THE RUNNING WATTS TOGETHER FOR ALL DEVICES. THIS IS THE MINIMUM RUNNING WATTAGE REQUIREMENT FOR YOUR NEEDS.

DEVICE	RUNNING WATTS
RV Air Conditioner (13,500 BTU)†	1250
LED/LCD Television	120
DVD Player	15
Slow Cooker	250
Cell Phone Charger	10
RV Microwave	600
Total	2245

GENERATOR SIZE

Minimum running Watts for your needs

2300 running Watts

	DEVICE	RUNNING WATTS
RECREATION	RV Air Conditioner (13,500 BTU)†	1250
	Cell Phone Charger	10
	Box Fan - 20"	100
	Tablet	20
	DVD Player	15
	LED/LCD Television	120
	Slow Cooker	250
	Laptop Computer	75
	Coffee Maker	900
	RV Microwave	600
	Blender	1000
	Hair Dryer	1500
JOBSITE	Lithium Ion Battery Charger	360
	Air Compressor†	1000
	Circular Saw†	1400
	Hand Drill†	600
	Belt Sander†	1200
	Reciprocating Saw†	1440
	Table Saw†	1800
	Airless Paint Sprayer	1080
	Wet Dry Vac	900
	Quartz Halogen Work Light	1000
HOUSEHOLD	Refrigerator/Freezer†	700
	Lights	600
	Desktop Computer	400
	Sump Pump†	2100
	Toaster	1200
	Window AC (12,000 BTU)†	3250

**Watts listed are approximate. Check your appliance for actual requirements.*
Total wattage requirements assumes intermittent starting of devices.
†Motor load, demands higher Watts at start-up.



CONTROL PANEL FEATURES

GENERATOR STATUS LIGHTS
Power, low-oil, and overload alerts

EASY START
Start/Stop/Choke dial makes starting quick and easy

ECO MODE
Uses less fuel and reduces sound

USB PORTS
Charge smart phones, tablets and other electronics

PARALLEL READY
Connect two inverters together for twice the power (parallel kit sold separately)

2300 WATTS 3000 STARTING WATTS
INVERTER GENERATOR

SPECIFICATIONS

Model Number	C0010030
Configuration	50ST/CSA
Running Watts	2300
Starting Watts	3000
Engine Displacement	149cc
Engine Type	OHV
Starting Method	Recoil Pull Start
Low Oil Shutdown	Yes
Fuel Tank	1.06 gal.
Run Time at 50% Load	4.5 hrs
Run Time at 25% Load	5.8 hrs
Rated Voltage	120V
Low Total Harmonic Distortion (THD)	Less than 3%
Outlets	(2) 20A 120V 5-20R, (1) 30A 120V L5-30R Twist Lock, (2) USB - 1A / 2.1A
Parallel Ready	Yes
Handle Style	Single, Molded Into Enclosure
Product Dimensions (L"xW"xH")	22.2 X 13.3 X 18.4
Product Weight	59.5 lbs
Warranty - Residential	3 Year Limited
Warranty - Commercial	1 Year Limited

All portable specifications and models subject to change. Please consult factory for availability.

CRAFTSMAN®

CRAFTSMAN® is a registered trademark of Stanley Black & Decker, Inc., used under license.
© 2018 CRAFTSMAN

Product manufactured by:
Generac Power Systems, Inc.
S45 W29290 Hwy 59
Waukesha, WI 53189